

Device: Sony BRC X400/X401



Introduction

A large number of parameters can be controlled on the Sony X400/X401 cameras.

This integration was done using Sony BRC X400 software version 1.0.

Please see the "PTZ Manual" at <https://www.skaarhoj.com/support/manuals/> to learn more about PTZ control in general from SKAARHOJ controllers and in particular network recommendations.


In this manual it is worth noticing that one should not add *additional* Device Cores to control multiple cameras. This is possible from the same Device Core but proper steps should be ensured (consecutive IP addresses on the cameras) for a good user experience.

Number of Cameras possible to control

Please notice from the Sony BRC X400 Device Core it is possible to control up to 7 cameras. In general this is the limit for our VISCA over IP Device Cores and our integration have not been tested above 7 cameras. If you want to control more than 7 cameras you will need to add an additional Device Core and configure the controller accordingly. None of our default configuration utilities use 2 x Sony BRC X400 Device Cores. As we have never tested with more than 7 cameras, we do not know how performance and stability will be in such a configuration setup. We recommend only having 1 x Sony BRC X400 Device Core installed per controller.

Confirm Connection

The Serial Monitor from the Firmware Application can be used to monitor connection status.



Device Configurations


Device configuration options exist:

- Index 0: **VISCA over IP/Serial**
 - If "1" = VISCA over Serial

Example:

Enabling VISCA over serial could look like this device configuration code: "D0:0=1" where the general form would be "Dx:y=z" where "x" is the number of the device core as installed on the controller (starting with zero for the first device core), "y" the index number and "z" the value for that index.

If the Sony BRC-400X Device Core is the first like below:



Save Settings

Setting VISCA over serial would be set by this configuration under “Manage Media” on the configuration page for your controller. Access this by pressing “Online Configuration” in the Firmware Application. Remember to save on the configuration page *and* press “Check for updates” in the Firmware Application.

Device Core Options

Some device cores support additional options that can be defined through this text field. Please refer to the manual for the particular device core for details.

To confirm that a device configuration is in fact detected by the controller, please check it out on the serial monitor where it will be mentioned:

```
Memory A-D restored
Compiled: Mar 12 2020 14:41:54
D0[0] = 1
DeviceCore #0: SONYBRCX4000, IP = 192.168.10.149
SONYBRCX400: Option serial
ClientVISCAserialIP: __deviceIdx: 0
ClientVISCAserialIP::begin()
setup() Done
-----
```

Actions

An excerpt of the actions in the Device Core

- Sony BRC-X400/X401: Pan
- Sony BRC-X400/X401: Tilt
- Sony BRC-X400/X401: Pan/Tilt
- Sony BRC-X400/X401: Zoom
- Sony BRC-X400/X401: Zoom (Binary)
- Sony BRC-X400/X401: Focus
- Sony BRC-X400/X401: Focus (Binary)
- Sony BRC-X400/X401: Focus One Push
- Sony BRC-X400/X401: PT Limit (Planned)
- Sony BRC-X400/X401: PT Slow Mode
- Sony BRC-X400/X401: Focus Settings
- Sony BRC-X400/X401: Zoom Settings
- Sony BRC-X400/X401: Exposure Mode
- Sony BRC-X400/X401: Iris
- Sony BRC-X400/X401: Shutter
- Sony BRC-X400/X401: Gain
- Sony BRC-X400/X401: AE Speed
- Sony BRC-X400/X401: Ex-Comp. Enable
- Sony BRC-X400/X401: Ex-Comp. Level
- Sony BRC-X400/X401: AE Comp
- Sony BRC-X400/X401: Gain Limit
- Sony BRC-X400/X401: Gain Point
- Sony BRC-X400/X401: Gain Point Pos
- Sony BRC-X400/X401: Max Shutter
- Sony BRC-X400/X401: Min Shutter
- Sony BRC-X400/X401: White Balance
- Sony BRC-X400/X401: WB One Push
- Sony BRC-X400/X401: WB Offset
- Sony BRC-X400/X401: WB Speed
- Sony BRC-X400/X401: WB R/B Gain
- Sony BRC-X400/X401: Matrix
- Sony BRC-X400/X401: Matrix Color
- Sony BRC-X400/X401: Chroma Suppress
- Sony BRC-X400/X401: Aperture Gain
- Sony BRC-X400/X401: Detail Auto
- Sony BRC-X400/X401: Detail Parameters
- Sony BRC-X400/X401: Knee
- Sony BRC-X400/X401: Knee Param
- Sony BRC-X400/X401: Noise Reduction
- Sony BRC-X400/X401: NR Settings
- Sony BRC-X400/X401: Gamma
- Sony BRC-X400/X401: Gamma Settings
- Sony BRC-X400/X401: Preset
- Sony BRC-X400/X401: Preset Drive
- Sony BRC-X400/X401: System
- Sony BRC-X400/X401: PTZ Cruise Control
- Sony BRC-X400/X401: PTZ Trace
- Sony BRC-X400/X401: Speed Limit
- Sony BRC-X400/X401: Auto Shift level
- Sony BRC-X400/X401: Camera Select